




Molded Case Circuit Breakers and Disconnect Switches Accessories for NZM 12...



1	2	3	4	5	6	
		Color of handle	Can be used with all devices of Type number	Type	Price	
					\$	
Handle for open or panel mounted devices Fastens to shaft, not padlockable			Gray	N(ZM)12...	H 12U	See Price List
			Black	N(ZM)12...	H 12U-SW	See Price List
Handle for Cover/Door Interlocking Degree of protection UL/NEMA 3R, 12; IEC IP 55 Door coupling rotary handle. For front mounting in doors and covers. Can be locked in the OFF position with up to three padlocks (hasp thickness 6 – 8 mm). Door/cover interlocking supplied standard set in OFF position. Can be field modified for setting in ON position. 3 distinct Handle positions: OFF - + (tripped) - ON Red -Yellow version for Emergency-Stop function.			Gray	N(ZM)12...	H 12-NA	See Price List
			Black	N(ZM)12...	H 12-SW-NA	See Price List
			Red/ Yellow	N(ZM)12...	RH 12-NA	See Price List
Extension shaft For mounting depths of 240 – 400 mm. Extends shaft length by 183 mm. Only one extension shaft possible. Can also be used with the mechanical interlock.				N(ZM)12...	A-NZM 12	See Price List
Switch position indicator Indicates position of switch when panel door is open.				N(ZM)12...	SA-NZM 12	See Price List
Maintenance Handle To actuate the device when the panel door is open.				N(ZM)12...	H 12UZ	See Price List
Mechanical Interlock For mechanical interlocking of two devices mounted side by side. Requires two handles, one for each switch. Order separately.				N(ZM)12...	KV-2 NZM 12	See Price List
For mechanical interlocking of two devices not mounted side by side. Requires two handles, one for each switch. Order separately.				N(ZM)12...	KVA-2 NZM 12	See Price List
For mechanically interlocking two main incomers with one emergency-supply device e.g. in emergency power supply systems. Handles ordered separately.				N(ZM)12...	KVA-3 NZM 12	See Price List

Disconnect Switches, Molded Case Switches

Circuit Breakers

Ordering Information:
 Specify Type from Column 5. Example: **H 12-SW-NA**
 If ordering with device, just add a "+" in front of the Type number. Example: **+ H 12-SW-NA**

Molded Case Circuit Breakers and Disconnect Switches Accessories for NZM 12...

1	2	3	4	5	6
	Color of handle	Can be used with all devices of Type number	Type To be ordered with device only. Add below suffix	Type	Price \$
<p>Rear operation shafts For side panel mounting where device is only accessible from the rear (e.g. sides of enclosure panels). Must be combined with Type H...R rear operation handles. Factory installed only. Order with device.</p>		N(ZM) 12...	+R-NZM 12		See Price List See Price List
<p>Operating Handle for rear operation Used with rear operation shaft. Degree of protection: UL/NEMA 3R, 12; IEC IP 55 Can be locked in the OFF position with up to three padlocks (hasp thickness 6 – 8 mm). No cover/door interlocking provisions. 3 distinct Handle positions: OFF - + (tripped) - ON Red -Yellow version for Emergency-Stop function.</p>	Gray	N(ZM) 12...	—	H 12-R-NA	See Price List See Price List
	Black	N(ZM) 12...	—	H 12-R-SW-NA	See Price List See Price List
	Red/ Yellow	N(ZM) 12...	—	RH 12-R-NA	See Price List See Price List
<p> Legend Plate (for mounting with operating handle) Silver-colored, black lettering</p>					
<p> Specify desired text. Height of letters: 3.5, 5, and 7 mm</p>		N(ZM) 12...	—	ZSSOND-NZM 12	See Price List See Price List
Blank (for engraving or printing)		N(ZM) 12...	—	ZS60-NZM 12	See Price List See Price List
<p>Main Disconnect Warning plates. English Inscription: “Main Switch- Open only in OFF position” Silver-colored, black lettering</p>		N(ZM) 12...	—	ZS62-NZM 12	See Price List See Price List
<p>Also available in other languages:</p>		N(ZM) 12...	—	ZS...-NZM 12	See Price List See Price List
<p>Afrikaans (81) Bulgarian (64) Czech (78) Danish (65) Dutch (67) Finnish (66) French (63) German (61) Greek (69) Hungarian (80) Italian (68) Norwegian (70) Polish (71) Portuguese (72) Romanian (73) Russian (74) Serbo-Croatian (76) Spanish (77) Swedish (75) Turkish (79)</p>					
<p>Insert key number into Type. Example: ZS63-NZM 12 (Inscription in French language)</p>					

Ordering Information:
Specify Type from Column 5. Example: **H 12-R-SW-NA**.
If ordering with device, just add a “+” in front of the Type number. Example: **+ H 12-R-SW-NA**
Note:
Items in Column 4 are factory installed and must be ordered with the device.

Molded Case Circuit Breakers and Disconnect Switches Accessories for NZM 12...

1	2 Type To be ordered with device only. Add suffix shown below	3 Type	4 Price \$
<p>Control Circuit Tap-Off Terminals Supplementary terminals attached to main terminals. 3 connections top and bottom. Factory addition only, must be ordered with device.</p>	+ST	—	See Price List See Price List See Price List
<p>Terminal Cover Provides shock hazard protection in the area of the field wiring power terminals. Can be used at top or bottom, one cover per side. Mandatory requirement on the supply side of Main Disconnect switches to provide protection against accidental contact with line side feed.</p>	—	H-NZM 12	See Price List See Price List See Price List
<p>Test Unit for NZM 12 Circuit-Breakers Supply terminal voltage can be selected from 120/220/240 V, 50/60 Hz. The portable test unit can be used to verify that the long time, instantaneous and short-time delayed tripping characteristics of the circuit-breaker are operating per preset values. Various test voltages simulate a short-circuit or an overload condition which would cause the circuit-breaker to trip out. All measuring and connection leads, as well as operating instructions, are supplied with the unit.</p>	—	P-NZM	See Price List See Price List See Price List See Price List See Price List

Disconnect Switches, Molded Case Switches

Circuit Breakers



Ordering Information:
Accessory in Column 2 can only be ordered with device. Specify Type suffix. Example: **+ ST**
Specify Type from Column 3. Example: **H-NZM 12**
If ordering with device, just add a "+" in front of the Type number. Example: **+ H-NZM 12**