



Powering Business Worldwide

pe.eaton.com

UL 1077 Industrial Miniature Circuit Breaker Accessory - Auxiliary Trip Indicating Contact

FAZ-XAM002

Dimensions:

- **Height:** 3.15 IN
- **Length:** .35 IN
- **Width:** 1.772 IN

Notes: Small selector screw changes mode. 2 Form C (changeover) contacts. Installs left side of FAZ/shunt trip. Aux contacts switch when FAZ is tripped electrically or manually. Trip indicating contact switches only when FAZ tripped electrically

Warranties:

- 1 year

Specifications:

- **Amperage Rating:** 4A
- **Voltage Rating:** 250V
- **Frequency Rating:** 50-60 Hz
- **Trip Type:** Trip-indicating
- **Protection:** IEC: IP20

Supporting documents:

- [Eatons Volume 4-Circuit Protection](#)
- [Industrial miniature circuit breakers UL 489](#)
- [Product Data Sheet - FAZ-XAM002](#)

Certifications:

- UL 1077
- IEC 60947-2
- EN 60947-2
- EN 60898
- CSA Std. C22.2 No. 235
- IEC 60898

Product compliance:

- CE Marked



