



Powering Business Worldwide

pe.eaton.com

XT Manual Motor Protection Accessories - Auxiliary Contact

XTPAXFAEM20

Dimensions:

- Height: X
- Length: X
- Width: X

Notes: Can be fitted to the front of a manual motor protector. 45 mm width of manual motor protector remains unchanged. For early energization of undervoltage release, e.g., in emergency-stop circuits to EN 60204.

Warranties: No Data

Specifications: No Data

Supporting documents:

- [Eatons Volume 5-Motor Control and Protection](#)
- [Eaton Specification Sheet - XTPAXFAEM20](#)
- [Global Data Sheet - XTPAXFAEM20](#)

Certifications: No Data

Product compliance: No Data

